



FAST-CHECK TUBE TESTER

TUBE CHART

Chart FC2 - 66915

Century Electronics Co., Inc.

manufacturers of electronic equipment

315 ROSLYN ROAD • MINEOLA, NEW YORK

COPYRIGHT 1966 - MERCURY ELECTRONICS CORPORATION



SYMBOLS USED IN NOTES COLUMN

A - Read quality on "SPECIAL" scale

B - Tube will glow

C - Disregard "SHORT" indication

D - Quality is good if meter reads
over "3" on numerical scale

E - Use clip with black wire

F - Clip to right hand top cap of tube

Tube Data Division

Mercury Electronics Corp., 1744 Rockaway Avenue, Hewlett, N. Y. 11557

TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket
OA2	L	65	41/B	1J6	A	40	7	2AV2	A	100	14/A	3AL5	B	36	36
OA3	L	70	10/BC	1K3	A	100	12/AD	2AZ2	A	100	13/A	3AU6	B	28	34
OB2	L	100	41/BC	1L4	A	50	35	2B3	B	100	12/A	3AV6	B	34	34
OB3	L	50	10/BC	1L6	A	66	35	2BA2	A	80	14/A	3B2	B	100	12/D
OC2	L	50	41/ABC	1LA4	A	47	29	2BN4	B	25	38	3BA6	B	30	34
OC3	L	100	10/BC	1LA6	A	54	28	2BJ2	B	100	13/A	3BC5	B	27	34
OD3	L	45	10/BC	1LB4	A	47	29	2CY5	B	26	34	3BE6	B	29	34
OZ4	L	32	10	1LC5	A	40	29	2D21	D	35	39	3BF6	B	39	35
1A5	A	55	5	1LC6	A	54	28	2DS5	B	32	39	3BN4	B	26	38
1A7	A	60	5	1LD5	A	49	29	2DZ4	B	29	40	3BN6	B	100	38/A
1AF4	A	41	35	1LE3	A	45	29	2E26	D	36	8	3BU8	B	30	22
1AH5	A	58	35	1LF3	A	45	29	2E30	D	44	39	3BX6	B	29	31
1AM4	A	45	35	1LG5	A	44	29	2EA5	B	27	34	3BY6	B	29	34
1AQ5	A	44	35	1LH4	A	49	29	2ER5	B	25	36/C	3BY7	B	29	31
1AS5	A	50	35	1LN5	A	47	29	2ES5	B	26	36/C	3BZ6	B	27	34
1AU3	A	95	10/AD	1N2	A	94	12/AD	2EV5	B	27	32	3C4	B	34	34
1AX2	A	100	13/D	1N5	A	49	5	2FH5	B	25	36/C	3C6	A	100	29/D
1B3	A	100	12/A	1P5	A	49	5	2FS5	B	27	34	3CA3	B	96	12/A
1BC2	A	100	13/D	1P10	B	41	35	2FV6	B	26	34	3CB6	B	28	34
1C1	A	44	35	1P11	B	39	35	2FY5	B	25	36/C	3CE5	B	29	34
1C5	A	45	5	1Q5	A	53	5	2GK5	B	26	36/C	3CF6	B	28	34
1C7	A	72	5	1R4	A	73	28	2GW5	B	25	40	3CS6	B	29	34
1D5	A	66	3	1R5	A	44	35	2GZ5	B	26	38	3CY5	B	27	34
1D8	A	38	7	1S2	A	100	13/A	2HA5	B	28	31	3DK6	B	27	34
1DN5	A	49	35	1S4	A	39	35	2HM5	B	39	35	3DT6	B	28	34
1F2	A	50	35	1S5	A	49	35	2T4	B	30	40	3DZ4	B	29	40
1F3	A	45	5	1SA6	A	47	4	2V3	B	100	12/A	3DZ11	B	21	2
1F5	B	45	5	1T4	A	45	35	3A2	B	100	13/A	3EA5	B	27	34
1FD9	A	49	35	1T5	A	48	5	3A3	B	100	12/A	3EH7	B	27	31
1G3	A	100	12/A	1U4	A	45	35	3A4	B	37	35	3EJ7	B	22	31
1G6	A	38	7	1U5	A	50	35	3A8)	B	50	4	3EM7	B	39	1
1H2	A	100	13/D	1U6	A	57	35	3A8)	B	40	8	3ER5	B	25	36/C
1H5)	A	51	4	1V2	A	100	14/A	3AF4	B	31	40	3ES5	B	26	36/C
1H5)	A	45	5	1X2	A	100	13/A	3AJ8)	B	28	27	3EV5	B	27	32
1J3	A	100	12/AD	2AF4	B	28	40	3AJ8)	B	33	20	3FH5	B	25	36/C

TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket
3FQ5	B	25	36/C	4GX6	C	27	34	5ES8	C	28	17	6AD6	D	100	3/B
3FQ7	B	45	17	4GX7	C	53	31	5EU8)	C	26	18	6AD7	D	51	3
3FS5	B	27	34	4GZ5	C	26	38	5EU8)	C	30	27	6AF3	D	30	14/E
3FY5	B	25	36/C	4HA5	C	28	31	5EV8	C	25	14	6AF4	D	29	40
3GK5	B	26	36/C	4HG8)	C	28	31	5EW6	C	27	34	6AF6	D	100	11/B
3GS8	B	29	22	4HG8)	C	28	17/C	5FG7	C	24	18	6AF9	D	31	25
3GW5	B	25	40	4HM5	C	26	34	5FV8	C	30	20	6AG5	D	27	34
3GZ5	B	26	38	4HM6	C	27	31	5GH8)	C	28	23	6AG7	D	27	2
3HA5	B	28	31	4HS8	C	29	22	5GH8)	C	30	14	6AG12	D	21	2
3HM5	B	26	34	4HT6	C	27	31	5GJ7	C	28	31	6AH4	D	85	3
3HM6	B	27	31	4JC6	C	27	31	5GM6	C	27	34	6AH6	D	28	34
3HS8	B	29	22	4JD6	C	27	31	5GX6	C	27	34	6AJ4	D	26	32
3HT6	B	27	31	4JK6	C	30	34	5GX7	C	53	31	6AJ5	D	42	34
3JC6	B	30	31	4JN8	C	30	20	5HB7	C	27	31	6AJ7	D	33	2
3JD6	B	30	31	4KE8	C	28	20	5HG8)	C	28	31	6AJ8)	D	28	27
3LF4	B	41	29	4LJ8)	C	21	14	5HG8)	C	28	17/C	6AJ8)	D	33	20
3Q4	B	36	35	4LJ8)	C	21	18	5HZ6	C	30	39	6AK5	D	29	34
3Q5	A	53	5	5AF4	C	28	40	5J6	C	29	34	6AK6	D	36	34
3S4	B	41	35	5AM8	C	35	16	5JK6	C	30	34	6AK7	D	27	2
3V4	B	39	35	5AN8	C	51	15/A	5KD8	C	33	20	6AK8)	D	50	19
3W4	B	41	35	5AQ5	C	33	39	5KE8	C	28	20	6AK8)	D	27	25
4A6	C	42	9	5AR4)	C	50	4	5KZ8	C	30	20	6AL3	D	28	16/C/E
4AU6	C	28	34	5AR4)	C	50	5	5LJ8)	C	21	14	6AL5	D	35	36
4AV6	C	32	34	5AR5	C	38	34	5LJ8)	C	21	18	6AL7	D	46	11
4BA6	C	30	34	5AS4)	C	50	4	5MB8	C	37	20	6AM4	D	32	32
4BC5	C	28	34	5AS4)	C	50	5	5R4)	C	50	4	6AM5	D	34	39
4BC8	C	30	15	5AS8	C	33	17	5R4)	C	50	5	6AM6	D	27	34
4BE6	C	30	34	5AT8	D	26	18	5T4)	C	43	4	6AM8	D	33	16
4BK7	C	30	15	5AU4)	C	55	4	5T4)	C	43	5	6AN4	D	25	40
4BL8	C	28	23	5AU4)	C	55	5	5T8)	C	49	19	6AN5	D	28	34
4BN4	C	26	38	5AV8	C	51	16/A	5T8)	C	28	25	6AN8	D	51	15/A
4BN6	C	100	38/A	5AW4)	C	55	4	5U4)	C	50	4	6AQ5	D	35	39
4BQ7	C	35	15	5AW4)	C	55	5	5U4)	C	50	5	6AQ6	D	37	34
4BS8	C	36	15	5AX4)	C	45	4	5U8	C	33	20	6AQ7	D	37	6
4BU8	C	29	22	5AX4)	C	45	5	5U9	C	34	33	6AQ8	D	30	17
4BX8	C	37	15	5B8	C	36	23	5V3)	C	45	4	6AR5	D	38	34
4BY6	C	28	34	5BC8	C	36	15	5V3)	C	45	5	6AR8	D	27	25
4BZ6	C	30	34	5BE8	C	31	20	5V4)	C	35	4	6AS5	D	36	38
4BZ7	C	34	15	5BK5	C	31	21	5V4)	C	35	5	6AS6	D	28	34
4BZ8	C	35	15	5BK7	C	32	15	5V6	C	32	3	6AS7	D	33	1
4CB6	C	26	34	5BM8	C	30	26	5V9	C	33	22	6AS8	D	33	17
4CE5	C	29	34	5BQ7	C	36	15	5W4)	C	55	4	6AT6	D	34	34
4CM6	C	37	25	5BR8	C	31	20	5W4)	C	55	5	6AT8	D	26	18
4CS6	C	28	34	5BS8	C	36	15	5X4)	C	50	6	6AU4	D	30	1
4CY5	C	27	34	5BT8)	C	26	22	5X4)	C	50	7	6AU5	D	38	9
4DE6	C	26	34	5BT8)	C	43	27	5X8	C	26	18	6AU6	D	27	34
4DK6	C	27	34	5BW8	C	26	25	5X9	C	35	33	6AU7	D	43	17
4DT6	C	28	34	5BZ7	C	33	15	5Y3)	C	65	4	6AU8	D	36	24
4DZ4	C	29	40	5CG8	C	26	18	5Y3)	C	65	5	6AV5	D	30	9
4EH7	C	27	31	5CL8	C	30	20	5Y4)	C	65	6	6AV6	D	32	34
4EJ7	C	22	31	5CM6	C	37	25	5Y4)	C	65	7	6AW8	D	35	24
4ER5	C	25	36/C	5CM8	C	37	20	5Z4)	C	35	4	6AX4	D	32	1
4ES8	C	28	17	5CQ8	C	31	20	5Z4)	C	35	5	6AX5	D	37	3
4EW6	C	26	34	5CR8	C	36	20	6A5	D	50	9	6AX7	D	44	17
4FY5	C	25	36/C	5CZ5	C	31	25	6A8	D	36	3	6AX8	D	31	20
4GJ7	C	28	31	5DH8	C	30	20	6AB4	D	27	34	6AZ8)	D	28	17/C
4GK5	C	26	36/C	5DJ4)	C	50	4	6AB7	D	33	2	6AZ8)	D	32	20
4GM6	C	25	34	5DJ4)	C	50	5	6AB8	D	40	27	6B4	D	49	5
4GS8	C	29	22	5EA8	C	32	20	6AC5	D	36	3	6B6	D	34	3
4GW5	C	25	40	5EH8	C	25	21	6AC7	D	33	2	6B8	D	44	3

TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket
6B-1000	D	30	34	6BY6	D	28	34	6DE7	D	53	30	6FD7	D	47	30
6BA6	D	29	34	6BY7	D	29	31	6DG6	D	31	3	6FD10	D	21	2
6BA7	D	28	18	6BY8)	D	30	17	6DJ8	D	31	17	6FE5	D	29	3
6BA8	D	34	24	6BY8)	D	100	22/A	6DK6	D	27	34	6FG5	D	26	34
6BC4	D	26	21	6BZ6	D	30	34	6DL4	D	38	16/A	6FG6	D	63	26/C
6BC5	D	26	34	6BZ7	D	33	15	6DL5	D	28	39	6FG7	D	24	18
6BC7)	D	28	22	6BZ8	D	35	15	6DL8)	D	60	14	6FH5	D	25	36/C
6BC7)	D	32	23	6C4	D	34	34	6DL8)	D	30	33	6FH6	D	32	3
6BC8	D	32	15	6C5	D	38	3	6DM4	D	31	1	6FH8	D	32	17
6BD4	D	60	3/A	6C8	D	39	3	6DN6	D	32	9	6FM8	D	46	19
6BD5	D	31	9	6CA4	D	27	18	6DN7	D	48	1	6FQ5	D	25	36/C
6BD6	D	33	34	6CA5	D	35	38	6DQ4	D	32	1	6FQ7	D	45	17
6BD7	D	35	27	6CA7	D	32	3	6DQ5	D	33	9	6FS5	D	27	34
6BE6	D	29	34	6CB5	D	32	9	6DQ6	D	31	3	6FV6	D	26	34
6BE7	D	32	15	6CB6	D	26	34	6DR7	D	42	30	6FV8	D	25	14
6BE8	D	31	20	6CD6	D	36	9	6DS5	D	32	39	6FW5	D	28	9
6BF5	D	38	39	6CE5	D	28	34	6DT4	D	27	1	6FW8	D	30	15
6BF6	D	39	34	6CF6	D	28	34	6DT5	D	37	25	6FY5	D	25	36/C
6BG6	D	32	9	6CG7	D	54	15	6DT6	D	28	34	6G6	D	35	3
6BH6	D	28	34	6CG8	D	28	18	6DT8	D	30	17	6GC5	D	29	25
6BH8	D	32	24	6CH6	D	33	18	6DW5	D	23	25	6GE8	D	28	33
6BJ6	D	29	34	6CH7	D	31	17	6DX8	D	26	18	6GH8)	D	28	23
6BJ7)	D	30	22	6CH8	D	36	24	6DY5	D	38	18	6GH8)	D	27	14
6BJ7)	D	37	23	6CK4	D	28	4	6DZ4	D	30	40	6GJ7	D	28	31
6BJ8)	D	32	22	6CK6	D	29	18	6DZ7	D	28	3	6GK5	D	26	36/C
6BJ8)	D	40	26	6CL5	D	32	9	6DZ8)	D	34	14	6GK6	D	29	31
6BK4	D	75	11/A	6CL6	D	28	31	6DZ8)	D	30	33	6GL7	D	37	1
6BK5	D	31	21	6CL8	D	30	20	6EA5	D	27	34	6GM5	D	30	25
6BK6	D	33	34	6CM4	D	31	20/C	6EA7	D	43	1	6GM6	D	25	34
6BK7	D	30	15	6CM5	D	28	5	6EA8	D	32	20	6GM8	D	34	17
6BL4	D	30	7	6CM6	D	37	25	6EB5	D	50	38	6GN8	D	43	24
6BL7	D	40	1	6CM7)	D	37	18	6EB8)	D	28	21	6GQ7)	D	31	22
6BL8	D	28	23	6CM7)	D	29	22	6EB8)	D	40	24	6GQ7)	D	37	23
6BM5	D	35	39	6CM8	D	40	20	6EH5	D	28	38	6GS8	D	29	22
6BM8)	D	29	33	6CN7)	D	35	21	6EH7	D	27	31	6GU7	D	38	15
6BM8)	D	31	14	6CN7)	D	27	27	6EH8	D	25	21	6GV7	D	29	18
6BN4	D	26	38	6CQ4	D	29	1	6EJ7	D	22	31	6GV8	D	38	20
6BN6	D	100	38/A	6CQ6	D	37	39	6EM5	D	32	25	6GW5	D	25	40
6BN8)	D	28	22	6CQ8	D	31	20	6EM7	D	39	1	6GW6	D	29	3
6BN8)	D	33	26	6CR6	D	35	38	6EQ7	D	30	27	6GW8	D	35	25
6BQ5	D	29	18	6CR8	D	35	20	6ER5	D	25	36/C	6GX6	D	27	34
6BQ6	D	29	3	6CS6	D	28	34	6ES5	D	26	36/C	6GX7	D	53	31
6BQ7	D	30	15	6CS7	D	51	30	6ES8	D	24	27	6GY6	D	26	34
6BR8	D	32	20	6CU5	D	36	38	6ET7	D	50	24/A	6GY8)	D	33	14
6BS3	D	28	22	6CU6	D	28	3	6EU8)	D	27	18	6GY8)	D	31	25/C
6BS8	D	35	15	6CU8	D	35	24	6EU8)	D	27	27	6GZ5	D	26	38
6BT6	D	32	34	6CW5	D	71	20	6EV5	D	24	34	6H6	D	69	8
6BT8)	D	43	27	6CX8	D	39	24	6EV7	D	30	17	6HA5	D	24	34
6BT8)	D	26	22	6CY5	D	27	34	6EW6	D	23	34	6HA6	D	28	31
6BU6	D	36	34	6CY7	D	44	30	6EW7	D	48	30	6HB6	D	28	31
6BU8	D	29	22	6CZ5	D	32	25	6EW8	D	30	17	6HB7	D	27	31
6BV8)	D	29	20/C	6DA4	D	29	1	6EX6	D	28	9	6HB8)	D	37	14
6BV8)	D	32	23	6DA5	D	55	25	6EY6	D	30	3	6HB8)	D	29	25
6BW4	D	46	22	6DA6	D	29	27	6EZ5	D	28	3	6HC8)	D	26	14
6BW6	D	38	18	6DB5	D	38	25	6EZ8	D	40	13	6HC8)	D	25	33
6BW8	D	26	25	6DB6	D	28	34	6F5	D	35	3	6HF8	D	32	24
6BX6	D	29	31	6DC6	D	28	34	6F6	D	40	3	6HG5	D	35	39
6BX7	D	40	1	6DC8	D	29	18	6F8	D	39	3	6HG8)	D	28	31
6BX8	D	37	15	6DE4	D	31	1	6FA7)	D	31	18	6HG8)	D	28	17/C
6BY5	D	31	3	6DE6	D	26	34	6FA7)	D	33	21	6HJ8	D	34	16

TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket
6HL5	D	30	27	6MB8	D	37	20	7AD7	D	28	28	8EM5	E	32	25
6HL8	D	35	20	6N7	D	33	3	7AF7	D	25	28	8ET7	E	50	24/A
6HM5	D	26	34	6N8	D	30	18	7AG7	D	28	28	8FQ7	E	44	17
6HM6	D	27	31	6P5	D	37	3	7AH7	D	27	28	8GJ7	E	28	31
6HR5	D	35	39	6Q5	D	41	3	7AK7	D	29	28	8GK6	E	29	31
6HS8	D	29	22	6Q7	D	34	3	7AU7	D	45	17	8GX7	E	53	31
6HT6	D	27	31	6R7	D	35	3	7B4	D	36	28	8HA6	E	28	31
6HU6	D	50	26/C	6R8)	D	49	19	7B5	D	58	28	8HG8)	E	28	31
6HU8	D	33	23	6R8)	D	28	25	7B6	D	32	29	8HG8)	E	28	17/C
6HW8	D	29	25	6S4	D	33	25	7B7	D	37	28	8JE8	E	33	24
6HZ6	D	30	39	6S7	D	36	3	7B8	D	34	28	8JK8	E	32	15
6HZ8	D	34	24	6S8	D	38	6	7C4	D	51	28	8JT8	E	41	24
6J4	D	28	37	6SA7	D	31	3	7C5	D	32	28	8KA8	E	28	17
6J5	D	34	3	6SB7Y	D	29	3	7C6	D	35	29	8KT8	E	33	24
6J6	D	26	34	6SC7	D	34	6	7C7	D	31	28	8LC8	E	31	27/C
6J7	D	39	3	6SD7	D	29	2	7DJ8	D	31	17	8LE8	E	32	20
6J8	D	29	3	6SF5	D	37	6	7E6	D	37	29	8SN7	E	47	1
6JA8	D	32	24	6SF7	D	35	1/A	7E7	D	38	28	8U9	E	34	33
6JC6	D	30	31	6SG7	D	29	2	7ES8	D	24	27	8X9	E	35	33
6JC8)	D	26	23	6SH7	D	29	2	7EY6	E	30	3	9A8	E	38	20
6JC8)	D	28	16	6SJ7	D	32	2	7F7	D	26	28	9AQ8	E	30	17
6JD6	D	30	31	6SK7	D	34	2	7G7	D	40	28	9AU7	E	43	17
6JE8	D	33	24	6SL7	D	54	1	7GV7	D	29	18	9BM5	E	35	39
6JH8	D	30	25	6SN7	D	47	1	7H7	D	28	28	9BR7	E	37	17
6JK6	D	30	34	6SQ7	D	72	7	7HG8)	D	28	31	9BR8	E	32	20
6JK8	D	32	15	6SR7	D	76	7	7HG8)	D	28	17/C	9BW6	E	38	18
6JN8	D	30	20	6SS7	D	38	2	7J7	D	28	28	9CG8	E	28	18
6JT8	D	41	24	6ST7	D	66	7	7K7	D	29	28	9CL8	E	32	20
6JU8	D	32	17	6SU7	D	54	1	7L7	D	30	28	9DZ8)	E	34	14
6JV8	D	36	24	6SV7	D	44	1	7N7	D	25	28	9DZ8)	E	30	33
6JW8	D	30	23	6SZ7	D	80	7	7Q7	D	28	28	9EA8	E	32	20
6JX8	D	27	18	6T4	D	28	40	7R7	D	31	28	9GV8	E	28	20
6K5	D	33	3	6T8)	D	50	19	7S7	D	29	28	9JW8	E	30	23
6K6	D	39	3	6T8)	D	27	25	7V7	D	37	28	9KC6	E	30	31
6K7	D	40	3	6U4	D	29	1	7W7	D	28	29	9KV8	E	35	24
6K8	D	31	3	6U6	D	34	3	7X6	D	24	28	9KZ8	E	30	20
6KA8	D	28	17	6U7	D	38	3	7X7	D	28	29	9U8	E	31	20
6KD8	D	33	20	6U8	D	29	20	7Y4	D	31	28	9V9	E	33	22
6KE8	D	28	20	6U9	D	34	33	7Z4	D	36	28	9X8	E	28	18
6KL8	D	37	18	6V3	D	31	13/E	8AU8	E	33	24	10BQ5	E	29	18
6KM8)	D	38	18	6V4	D	30	18	8AW8	E	32	24	10C8	E	70	15/A
6KM8)	D	32	21	6V6	D	31	3	8B8	E	36	23	10CL8	E	30	20
6KR8	D	31	24	6V7	D	39	3	8BA8	E	34	24	10CW5	E	71	20
6KT8	D	33	24	6V8	D	32	31	8BH8	E	32	24	10DE7	E	50	30
6KU8	D	45	24	6V9	D	33	22	8BN8)	E	29	22	10DX8	E	26	18
6KV8	D	35	24	6W4	D	29	1	8BN8)	E	33	26	10EB8)	E	28	21
6KX8)	D	36	25	6W6	D	33	3	8BQ5	E	29	18	10EB8)	E	40	24
6KX8)	D	37	14	6X4	D	32	34	8BQ7	E	30	15	10EG7	E	43	1
6KZ8	D	30	20	6X5	D	31	3	8CG7	E	54	15	10EW7	E	49	30
6L6	D	38	3	6X8	D	25	18	8CM7)	E	37	18	10FD7	E	52	30
6L7	D	33	3	6X9	D	35	33	8CM7)	E	30	22	10GF7	E	30	15
6LB8	D	31	24	6Y6	D	38	3	8CN7)	E	36	21	10GH8)	E	28	23
6LE8	D	32	20	6Y9	D	31	24	8CN7)	E	26	27	10GH8)	E	27	14
6LF8	D	37	24	6ZY5)	D	40	4	8CS7	E	55	30	10GK6	E	29	31
6LJ8)	D	21	14	6ZY5)	D	40	5	8CW5	E	69	20	10GN8	E	49	24
6LJ8)	D	21	18	7A4	D	33	28	8CX8	E	38	24	10HA6	E	28	31
6LM8	D	35	20	7A5	D	31	28	8CY7	E	44	30	10HF8	E	32	24
6LN8	D	31	23	7A6	D	30	28	8DX8	E	26	18	10JA8	E	35	24
6LQ8	D	30	24	7A7	D	35	28	8EB8)	E	38	24	10JT8	E	41	24
6LX8	D	30	23	7A8	D	33	28	8EB8)	E	28	21	10JY8	E	30	24

TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket
10KR8	E	31	24	12BE6	F	27	34	12DZ6	F	26	34	12SX7	F	48	1
10KU8	E	45	24	12BE8	F	31	20	12DZ8)	F	34	14	12U7	F	41	17
10LB8	E	31	24	12BF6	F	40	34	12DZ8)	F	30	33	12V6	F	34	3
10LE8	E	32	20	12BH7	F	36	17	12EA8	F	25	34	12W6	F	30	3
10LW8	E	37	24	12BK5	F	31	21	12EC8	F	31	20	12X4	F	31	34
10LZ8	E	35	24	12BK6	F	35	34	12ED5	F	30	38	13CM5	F	28	5
11BM8)	F	29	33	12BL6	F	30	34	12EG6	F	28	34	13CW9	F	21	2
11BM8)	F	31	14	12BL7	F	40	1	12EH5	F	28	38	13DE7	F	50	30
11C5	F	33	38	12BM5	F	35	39	12EK6	F	26	34	13DR7	F	44	30
11CY7	F	44	30	12BN6	F	100	38/A	12EL6	F	32	34	13EM7	F	37	1
11JE8	F	33	24	12BQ6	F	29	3	12EM6	F	31	25	13FD7	F	52	30
11KV8	F	35	24	12BR7	F	32	17	12EN6	F	30	3	14A4	F	33	28
11LQ8	F	30	24	12BS3	F	30	22	12EQ7	F	30	27	14A5	F	39	28
11Y9	F	31	25	12BU6	F	36	34	12EZ6	F	26	34	14A7	F	37	28
12A4	F	29	22	12BV7	F	29	31	12F5	F	55	3	14AE7	F	43	28
12A6	F	37	3	12BW4	F	46	22	12F8)	F	75	23/A	14AF7	F	27	28
12A8	F	36	3	12BY7	F	29	31	12F8)	F	79	25	14B6	F	33	29
12AB5	F	32	25	12BZ7	F	32	17	12FK6	F	28	34	14B8	F	32	28
12AC5	F	36	3	12C5	F	35	38	12FM6	F	30	34	14C5	F	33	28
12AC6	F	34	34	12C8	F	44	3	12FQ8	F	36	30	14C7	F	31	28
12AD6	F	29	34	12CA5	F	35	38	12FR8)	F	25	33/C	14E6	F	37	29
12AD7	F	42	17	12CM6	F	37	25	12FR8)	F	29	25/C	14E7	F	40	28
12AE6	F	37	34	12CN5	F	29	38	12FX8)	F	29	23	14F7	F	26	28
12AE7	F	25	27	12CR6	F	34	38	12FX8)	F	30	25	14GT8	F	50	19
12AF3	F	30	14/E	12CS6	F	28	34	12G4	F	33	34	14GW8	F	35	25
12AF4	F	28	40	12CT8	F	43	15/A	12GA6	F	28	34	14H7	F	31	28
12AF6	F	29	34	12CU5	F	33	38	12GC5	F	29	25	14J7	F	31	28
12AG6	F	28	34	12CU6	F	31	3	12GC6	F	29	9	14JG8	F	39	19
12AJ6	F	33	34	12CX6	F	25	34	12GN7	F	27	31	14K7	F	29	28
12AJ7	F	31	18	12D4	F	29	1	12GW6	F	29	3	14L7	F	30	28
12AJ8)	F	28	27	12DA6	F	29	27	12H4	F	33	34	14N7	F	26	28
12AJ8)	F	33	20	12DB5	F	31	25	12H6	F	69	8	14Q7	F	29	28
12AK7	F	44	17	12DE8)	F	35	22/A	12HG7	F	33	31	14R7	F	30	28
12AL5	F	33	36	12DE8)	F	29	33	12HL5	F	30	27	14S7	F	29	28
12AL8)	F	16	33/A	12DF7	F	42	17	12HU8	F	33	23	14V7	F	37	28
12AL8)	F	54	22	12DJ8	F	31	17	12J5	F	33	3	14W7	F	28	29
12AQ5	F	35	39	12DK6	F	27	34	12J7	F	39	3	14X7	F	30	29
12AS5	F	36	38	12DK7	F	30	25	12J8	F	25	25	14Y4	F	31	28
12AT6	F	35	34	12DL8)	F	30	33	12JN8	F	30	20	15CW5	G	69	20
12AT7	F	30	17	12DL8)	F	60	14	12K5	F	29	38	15DQ8	G	29	18
12AU5	F	38	9	12DM7	F	44	17	12K7	F	37	3	15EW6	G	23	34
12AU6	F	28	34	12DQ4	F	32	1	12K8	F	31	3	15EW7	G	49	30
12AU7	F	44	17	12DQ6	F	32	3	12KL8	F	31	18	15FO7	G	21	2
12AU8	F	36	24	12DQ7	F	28	31	12L6	F	35	3	15HA6	G	28	31
12AV5	F	30	9	12DS7)	F	85	14	12Q7	F	33	3	15HG8)	G	28	31
12AV6	F	32	34	12DS7)	F	40	27/A	12R5	F	33	38	15HG8)	G	28	17/C
12AV7	F	33	17	12DS7)	F	90	14	12S8	F	35	6	15LE8	G	32	20
12AW6	F	31	34	12DT5	F	37	25	12SA7	F	32	3	16A5	G	30	18
12AX4	F	33	1	12DT6	F	28	34	12SC7	F	34	6	16A8)	G	29	33
12AX5	F	37	3	12DT7	F	44	17	12SF5	F	35	6	16A8)	G	31	14
12AX7	F	44	17	12DT8	F	30	17	12SF7	F	33	1/A	16AQ3	G	28	16/C/E
12AX12	F	21	2	12DU7	F	27	25	12SG7	F	29	2	16GK6	G	29	31
12AY7	F	48	17	12DV7	F	100	23/A	12SH7	F	29	2	16Y9	G	31	25
12AZ7	F	31	17	12DV8)	F	52	14	12SJ7	F	33	2	17A5	G	32	9
12B4	F	27	22	12DV8)	F	33	33	12SK7	F	36	2	17AU5	G	38	9
12B7	F	37	28	12DW5	F	23	25	12SL7	F	54	1	17AV5	G	30	9
12BA6	F	29	34	12DW7	F	39	17	12SN7	F	46	1	17AX4	G	32	1
12BA7	F	27	18	12DW8	F	28	17	12SQ7	F	72	7	17BQ6	G	28	3
12BD5	F	31	9	12DY7	F	44	17	12SR7	F	76	7	17BS3	G	29	22
12BD6	F	33	34	12DY8	F	27	25	12SS7	F	38	2	17BY7	G	29	31

TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket
17C5	G	35	38	25AC5	H	25	3	50BK5	J	32	21	5727	D	35	39
17CA5	G	35	38	25AU4	H	30	1	50BM8)	J	29	33	5732	D	40	3
17CU5	G	33	38	25AV5	H	32	9	50BM8)	J	31	14	5749	D	30	34
17D4	G	30	1	25AX4	H	33	1	50C5	J	33	38	5750	D	29	34
17DE4	G	31	1	25BK5	H	34	21	50C6	J	34	3	5751	F	46	17
17DG6	G	31	3	25BQ6	H	33	3	50CA5	J	35	38	5814	F	42	17
17DM4	G	31	1	25C5	H	36	38	50CD6	J	36	9	5824	H	30	3
17DQ4	G	32	1	25CA5	H	35	38	50DC4	J	28	37	5844	D	25	34
17DQ6	G	27	3	25CD6	H	33	9	50EH5	J	26	38	5852	D	31	3
17EW3	G	30	17	25CU6	H	32	3	50FK5	J	30	38	5871	D	31	3
17GW6	G	29	3	25D4	H	29	1	50HC6	J	29	38	5879	D	41	18
17GT6	G	21	2	25DK4	H	27	37	50HK6	J	31	38	5881	D	39	3
17H3	G	33	22	25DN6	H	34	9	50JY6	J	30	7	5910	A	45	35
17HC8)	G	28	14	25DQ6	H	30	3	50L6	J	28	3	5915	D	29	34
17HC8)	G	25	33	25DT5	H	37	25	50X8	J	24	28	5931)	C	50	4
17JK8	G	32	15	25EC6	H	29	9	50Y6	J	31	3	5931)	C	50	5
17L6	G	31	3	25EH5	H	28	38	50Y7	J	38	8	5932	D	32	3
17R5	G	33	38	25F5	H	35	38	60FX5	J	28	38	5963	F	44	17
17W6	G	31	3	25L6	H	35	3	60HL5	J	30	27	5964	D	21	34
17Z3	G	30	14/E	25U4	H	33	1	70L7)	J	43	2/AC	5965	F	33	17
18A5	G	31	9	25W4	H	31	1	70L7)	J	30	3	5992	D	30	3
18AK5	G	29	34	25W6	H	30	3	117L7)	K	35	2/C	5993	D	32	34
18AQ5	G	35	39	25Z6	H	40	8	117L7)	K	31	3	5998	D	30	1
18DZ8)	G	34	14	26A6	H	29	34	117M7)	K	35	2/C	6005	D	37	39
18DZ8)	G	30	33	26BK6	H	35	34	117M7)	K	32	3	6006	D	29	2
18FW6	G	28	34	26C6	H	39	34	117N7	K	28	3	6028	D	29	34
18FX6	G	28	34	26D6	H	33	34	117P7	K	36	3	6046	H	35	3
18FY6	G	31	34	26Z5W	H	42	17	117Z3	K	29	39	6057	F	49	17
18GV8	G	28	20	28HA6	H	28	31	117Z4	K	27	11	6058	D	35	36
18HB8)	G	37	14	29GK6	H	29	31	117Z6	K	35	8	6060	F	30	26
18HB8)	G	29	25	30CW5	I	69	20	884	D	43	3	6063	D	32	34
18J6	G	26	34	31BX7	I	40	1	1203A	D	51	28	6065	D	28	34
19AQ5	G	35	39	32A8	I	36	3	1232	D	33	28	6066	D	34	34
19AU4	G	31	1	32ET5	I	33	38	1280	F	28	28	6067	F	44	17
19BG6	G	31	9	32L7	I	33	3	1611	D	37	3	6072	F	46	17
19BQ7	G	30	15	34GD5	I	44	38	1612	D	33	3	6080	D	39	1
19C8)	G	47	19	35A5	I	30	28	1614	D	38	3	6094	D	37	44
19C8)	G	28	25	35B5	I	32	39	1620	D	38	3	6095	D	37	39
19CL8	G	30	20	35C5	I	31	38	1621	D	38	3	6096	D	41	34
19DE7	G	53	30	35CD6	I	36	9	1622	D	39	3	6097	D	35	36
19EA8	G	31	20	35DZ8)	I	34	14	1629	F	27	11	6099	D	28	34
19EZ8	G	40	13	35DZ8)	I	30	33	1632	F	35	3	6100	D	34	34
19GK6	G	29	31	35EH5)	I	27	38	1639	D	35	29	6101	D	29	34
19GQ7)	G	31	22	35EH5)	I	26	38	1852	D	36	2	6106)	C	65	4
19GQ7)	G	37	23	35FH5	I	25	36/C	1853	D	30	2	6106)	C	65	5
19HV8	G	37	20	35GL6	I	35	36	2050	D	35	5	6113	D	54	1
19J6	G	29	34	35HB8)	I	37	14	5595	D	29	34	6118	D	34	3
19JN8	G	28	14	35HB8)	I	29	25	5610	D	30	34	6134	D	33	2
19KG8G	G	28	20	35L6	I	31	3	5651	L	70	10/BC	6135	D	32	34
19T8)	G	49	19	35W4	I	29	37	5654	D	41	34	6136	D	27	34
19T8)	G	28	25	35Y4	G	28	29	5679	D	30	28	6137	D	32	2
19V8	G	32	31	35Z3	I	28	29	5686	D	35	23	6146	D	26	11
19X8	G	28	18	35Z4	I	28	11	5687	F	28	18	6180	D	47	1
19Y3	G	30	18	35Z5	I	26	11	5691	D	49	1	6186	D	27	34
20EQ7	G	30	27	36AM3	I	30	37	5692	D	46	1	6187	D	28	34
20EW7	G	49	30	421A	D	30	1	5693	D	33	2	6189	F	44	17
21AK6	G	36	34	45B5	J	35	39	5696	D	38	39	6201	F	30	17
21EX6	G	30	9	45Z3	J	33	39	5721	D	35	39	6202	D	32	34
21HB3	G	21	2	50A5	J	29	28	5725	D	29	34	6203	D	36	20
22DE4	G	31	1	50B5	J	35	39	5726	D	34	36	6211	F	35	17

TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket
6216	D	31	31	7581	D	38	3	DL95	B	36	35	ECH200	D	33	22
6227	D	33	27	7591	D	29	2	DL96	A	100	35/A	ECL82)	D	31	14
6265	D	28	34	7643)	D	29	14	DP61	D	29	34	ECL82)	D	29	33
6267	D	33	18	7643)	D	29	23	DY30	A	100	12/A	ECL84	D	26	18
6336	D	33	1	7695	I	28	25	DY80	A	100	13/A	ECL86	D	35	25
6360	F	33	25	7699	D	40	25	DY86	A	90	34/CD	ED2	D	35	36
6394	H	31	3	7701	F	39	23	DY87	A	100	13/A	EF22	D	35	14
6485	D	28	34	7716	F	36	24	E80CF)	D	29	14	EF80	D	25	31
6516	D	34	39	7717	D	27	34	E80CF)	D	27	23	EF85	D	25	31
6520	D	33	1	7724	F	50	19	E80L	D	33	27	EF86	D	33	18
6550	D	39	3	7728	F	30	17	E83F	D	27	27	EF91	D	27	34
6660	D	30	34	7729	F	44	17	E88CC	D	31	17	EF93	D	29	34
6661	D	29	34	7730	F	44	17	E91H	D	27	34	EF94	D	27	34
6662	D	29	34	7731	D	29	20	E180CC	F	24	27	EF95	D	29	34
6663	D	34	36	7732	D	26	34	E180F	D	25	31	EF96	D	27	34
6664	D	27	34	7733	F	29	33	E182CC	F	25	18	EF183	D	27	31
6669	D	35	39	8016	A	100	12/A	EEA91	D	35	36	EF184	D	22	31
6676	D	26	34	8106	F	24	22	EAA901	D	35	36	EF804	D	33	20
6677	D	29	31	8113	D	28	34	EABC80)	D	50	19	EFL200	D	31	25
6678	D	29	20	8298	D	26	11	EABC80)	D	27	25	EH90	D	28	34
6679	F	31	17	9001	D	36	34	EAF801)	D	29	27	EH900-S	D	29	34
6680	F	41	17	9002	D	37	40	EAF801)	D	95	19	EK11	D	21	2
6681	F	42	17	9003	D	34	34	EB34	D	69	8	EK90	D	29	34
6686	D	28	27	9006	D	51	37	EB91	D	35	36	EL34	D	32	3
6687	D	27	34	B36	F	46	1	EBC33	D	35	29	EL37	D	39	3
6688	D	25	31	B65	D	47	1	EBC90	D	34	34	EL83	D	29	18
6689	D	27	27	B152	F	30	17	EBC91	D	32	34	EL84	D	29	18
6853)	C	65	4	B309	F	30	17	EBF80	D	30	18	EL90	D	35	39
6853)	C	65	5	B329	F	44	17	EBF89	D	29	18	EL91	D	34	39
6883	F	30	8	BPMO4	D	35	39	EC88	D	55	16/A	EL95	D	28	39
6893	F	36	8	CK5726	D	35	36	EC90	D	29	34	EL821	D	33	18
6922	D	31	17	D63	D	69	8	EC91	D	35	36	ELL80	D	32	23
6927	D	26	34	D77	D	35	36	EC92	D	27	34	EM34	D	80	11/AB
6928	D	35	39	D152	D	35	36	EC95	D	25	36/C	EM35	D	0	11/B
6968	D	29	34	D717	D	35	36	EC97	D	25	36/C	EM80	D	53	25
6973	D	35	33	DAC32)	A	51	4	ECC33	D	41	1	EM81	D	55	25
7025	F	49	17	DAC32)	A	45	5	ECC35	D	54	1	EM84	D	63	26/C
7027	D	33	5	DAF91	A	49	35	ECC81	F	30	17	EQ80	D	32	15
7036	D	29	34	DAF92	A	50	35	ECC82	F	41	17	EY81	D	31	13/E
7055	F	31	36	DAF96	A	58	35	ECC83	F	42	17	EY88	D	28	16/C/E
7056	F	25	34	DC90	A	42	35	ECC85	D	30	17	EZ35	D	31	3
7057	F	26	27	DD6	D	35	36	ECC86	D	34	17	EZ80	D	30	18
7058	F	45	17	DDR7	D	34	28	ECC88	D	31	17	EZ81	D	33	18
7059	F	30	20	DF33	A	49	5	ECC91	D	26	34	EZ90	D	32	34
7060)	F	29	18	DF91	A	45	35	ECC189	D	24	27	GZ30)	C	35	4
7060)	F	24	22	DF92	A	50	35	ECC801-S	F	30	17	GZ30)	C	35	5
7061	F	42	25	DF96	A	40	35	ECC802-S	F	44	17	GZ32)	C	35	4
7062	F	24	27	DF904	A	45	35	ECC808)	D	37	14	GZ32)	C	35	5
7105	D	39	1	DH63	D	34	3	ECC808)	D	36	25	GZ34)	C	50	4
7119	F	25	18	DH77	D	34	34	ECF80	D	28	23	GZ34)	C	50	5
7167	D	27	34	DH149	D	31	28	ECF82	D	34	20	H52)	C	50	4
7189	D	29	18	DK32	A	60	5	ECF86)	D	28	31	H52)	C	50	5
7193	D	31	3/F	DK91	A	44	35	ECF86)	D	28	17/C	H63	D	35	3
7199	D	25	18	DK96	A	44	35	ECF200	D	35	33	HABC80)	G	49	19
7247	F	44	17	DL33	A	53	5	ECF201	D	34	33	HABC80)	G	28	25
7316	F	46	17	DL35	A	45	5	ECF801	D	28	31	HBC90	F	35	34
7355	D	31	2	DL91	A	39	35	ECF802	D	30	23	HBC91	F	32	34
7370	I	26	18	DL92	B	41	35	ECH81)	D	28	27	HCC85	G	30	17
7408	D	31	3	DL93	B	37	35	ECH81)	D	33	20	HCH42	F	29	28
7543	D	27	34	DL94	B	39	35	ECH84	D	27	18	HCH81	F	31	18

TUBE	Select.	Load	Notes Socket	TUBE	Select.	Load	Notes Socket
HF93	F	29	34	UF41	A	100	12/A
HF94	F	28	34	UF89	F	27	27
HK90	F	27	34	UL84	I	27	27
HL92	J	33	38	V2M70	D	32	34
HMD4	D	29	34	VR75	L	53	10/BC
HMO4	D	29	34	VR90	L	53	10/BC
HY90	I	29	37	VR105	L	100	10/BC
KT32	H	35	3	VR150	L	45	10/BC
KT63	D	40	3	VT90	D	72	8
KT66	D	26	3	W17	A	45	35
KT88	D	29	3	W179	D	29	31
KTW63	D	40	3	X17	A	45	35
L63	D	34	3	X63	D	36	3
L77	D	34	34	X155	D	35	15
LCF200	C	35	33	XC95	B	25	36/C
LCF201	C	34	33	XCC189	C	28	17
LCF801	C	28	31	XCF801	C	28	31
LCF802	D	30	22	XF183	B	27	31
LCH200	C	33	22	XF184	B	22	31
LFL200	F	31	25	XXB	A	100	29/D
N17	B	41	35	XXD	F	29	28
N18	B	37	8	XXFM	D	32	29
N19	B	39	35	XXL	D	33	28
N77	D	35	36	YC98	D	21	2
N144	D	34	39	YF183	C	27	31
N727	D	35	39	YF184	C	22	31
PC88	C	55	16/A	Z63	D	39	3
PCC85	E	30	17	Z152	D	29	31
PCC88	D	31	17	ZD17	A	49	35
PCC189	E	28	17	ZD19	A	49	35
PCF80	E	38	20				
PCF82	E	30	20				
PCF200	E	35	33				
PCF201	E	34	33				
PCF801	E	28	31				
PCF802	E	30	23				
PCH200	E	33	22				
PCL80	D	33	20				
PCL82)	G	29	33				
PCL82)	G	31	14				
PFL200	G	31	25				
PL21	D	35	39				
PL82	G	30	18				
PMO4	D	29	34				
PMO5	D	29	34				
PY81	G	30	14/E				
PY82	G	30	18				
QQVO3-10	F	33	25				
U41	A	90	12/D				
U50)	C	65	4				
U50)	C	65	5				
U52)	C	50	4				
U52)	C	50	5				
U78	D	32	34				
U147	D	31	3				
UBC41	F	30	28				
UCC85	H	31	17				
UCH42	F	29	28				
UCL82)	J	29	33				
UCL82)	J	31	14				

7071

MERCURY ELECTRONICS CORP.

Tube Test Data Division

1744 Rockaway Avenue

Hewlett, L.I., N.Y. 11557

09-22-70

NEW TUBE RELEASES
for use with
CHART FC1 & FC2 - 69615

TUBE	Select	Load	Socket Notes
3CY3	B	100	12/D
3CZ3	B	100	12/A/C
3DB3	B	100	12/D
3DC3	B	100	12/A
4GS7	C	30	18
4MK8	C	38	22
6EL4	D	19	11/A
6MQ8)	D	28	23
6MQ8)	D	29	14
6R-A6	D	25	24
8A8	E	38	20
10LM8	E	35	20
10LY8	E	35	24
11DS5	F	32	39
12DZ7	F	28	3
12JQ6	F	27	22
17JQ6	G	27	22
17Y9	G	31	25
19BX6	G	29	31
19DC8	G	29	18
19FX5	G	30	38
25JQ6	H	27	22
26AQ8	H	31	17
26HU5	H	32	6

701215

MERCURY ELECTRONICS CORP.
 Tube Test Data Division
 1744 Rockaway Avenue
 Hewlett, L. I., N. Y. 11557

NEW TUBE RELEASES
 for use with
 CHART FC1 & FC2 - 69615

TUBE	Select	Load	Socket Notes
3CY3	B	100	12/D
3CZ3	B	100	12/A/C
3DB3	B	100	12/D
3DC3	B	100	12/A
6EL4	D	19	11/A
6MG8	D	37	20
6MQ8)	D	28	23
6MQ8)	D	29	14
6MU8)	D	30	23
6MU8)	D	30	14
8MU8)	E	30	23
8MU8)	E	30	14
11DS5	F	32	39
12DZ7	F	28	3
12JQ6	F	27	22
17JQ6	G	27	22
19DC8	G	29	18
19FL8	G	29	18
25JQ6	H	27	22
26HU5	H	32	6

FOREIGN

UBF-89	G	29	18
XL-86	E	69	20

NEW TUBE LISTING FOR FAST-CHECK TUBE TESTER

The following new tubes should be added to your FAST CHECK tube chart:

<u>TUBE</u>	<u>SELECTOR</u>	<u>LOAD</u>	<u>SOCKET</u>	<u>NOTES</u>
5FG7.....	C	24	18	
5FV8.....	C	30	20	
6DZ7.....	D	28	3	
6EZ5.....	D	28	3	
6FA7.....	D	33	21	
6FG7.....	D	24	18	
6FM8.....	D	46	19	
6FS5	D	27	34	
6FW5.....	D	28	9	
6GE8.....	D	28	33	
6GN8.....	D	43	24	
6HS8	D	29	22	
12DS7.....	F	90	14	
12DV7.....	F	100	23	A
12EZ6.....	F	26	34	
12FR8}.....	F	25	33	C
12FR8}.....	F	29	25	C
12GA6	F	28	34	
13DR7	F	44	30	
13EM7	F	37	1	
14GT8	F	50	19	
19HV8	G	37	20	
25DK4	H	27	37	
35EH5	I	27	38	
5686	D	35	23	
7355	D	31	2	
7701	F	39	23	
7716	F	36	24	

ADDITIONAL LISTINGS WILL BE RELEASED AS NEW TYPES ARE INTRODUCED.

681015

MERCURY ELECTRONICS CORP.
 Tube Test Data Division
 1744 Rockaway Avenue
 Hewlett, L.I., N.Y. 11557

NEW TUBE RELEASES
 for use with
 CHART FC2 - 68305

TUBE	Select	Load	Socket Notes
1BG2	A	100	13/A
Insert leads into pins 4&5 of socket. lead goes to cap.			Top
3CU3	B	100	12/A
3KF8	B	27	22
4KF8	C	27	22
6HD7	D	22	31
6JQ6	D	20	22
6KF8	D	27	22
6KT6	D	30	31
6LD6	D	24	31
6MK8	D	38	22
6R4	D	38	18
9KX6	E	32	31
9LA6	E	32	31
10GV8	E	38	20
13FR7	F	46	30
17BR3	G	30	14/E
19JC6	G	30	31
5642	A	100	13/A
Insert leads into pins 4&5 of socket. lead goes to cap.			Top
7788	D	27	31/C
8102)	F	30	14
8102)	F	30	33
EL-802	D	24	31
LCL-80	C	32	18
LY-81	F	31	13/E

Century Electronics Co., Inc.

manufacturers of electronic equipment



111 ROOSEVELT AVE., MINEOLA, N. Y.

Pioneer 2-5400

TO: All FAST-CHECK tube tester owners

SUBJECT: New tube listings

The following new tube types have been introduced and their settings should be added to your FAST-CHECK Tube Chart:

<u>TUBE</u>	<u>SELECT.</u>	<u>LOAD</u>	<u>SOCKET</u>	<u>NOTES</u>	<u>TUBE</u>	<u>SELECT.</u>	<u>LOAD</u>	<u>SOCKET</u>	<u>NOTES</u>
1S2	A	100	13	A	22DE4	G	31	1	
4EW6	C	26	34		32ET5	I	33	38	
6DA4	D	29	1		35EH5	I	26	38	
6DE4	D	31	1		36AM3	I	30	37	
6DR7	D	42	30		DAC32)	A	51	4	
6DW5	D	23	25		DAC32)	A	45	5	
6EA7	D	43	1		DF33	A	49	5	
6ER5	D	23	36	C	DF91	A	45	35	
6ES5	D	23	36	C	DF92	A	50	35	
6EV5	D	24	34		DF96	A	40	35	
6EV7	D	30	17		DK32	A	60	5	
6EX6	D	28	9		DK96	A	44	35	
6EY6	D	30	3		DL33	A	53	5	
6EZ8	D	40	13		DL35	A	45	5	
6FH8	D	32	17		DL92	B	41	35	
6FW8	D	30	15		DL96	A	100	35	A
6GH8)	D	28	23		E88CC	D	31	17	
6GH8)	D	27	14		EAA901	D	35	36	
10EB8)	E	28	21		EF80	D	25	31	
10EB8)	E	40	24		EF85	D	25	31	
12AJ8)	F	28	27		EL95	D	28	39	
12AJ8)	F	33	20		KT38	D	29	3	
12AS5	F	36	38		PCF82	E	30	20	
12DT6	F	28	34		5964	D	21	34	
12DW8	F	28	17		5992	D	30	3	
12DY8	F	27	25		6072	F	46	17	
12EA6	F	25	34		6080	D	39	1	
12EC8	F	31	20		6097	D	35	36	
12FK6	F	28	34		6135	D	32	34	
12FQ8	F	36	30		6137	D	32	2	
17DE4	G	31	1		6189	F	44	17	
18FW6	G	28	34		6203	D	36	20	
18FX6	G	28	34		7055	F	31	36	
18FY6	G	31	34		7056	F	25	34	
19CL8	G	30	20		7058	F	45	17	
19DE7	G	53	30		7059	F	30	20	
19EA8	G	31	20						

CENTURY

671019
(Replaces 67519 Issue)

MERCURY ELECTRONICS CORP.
Tube Test Data Division
1744 Rockaway Avenue
Hewlett, L. I., N. Y. 11557

NEW TUBE RELEASES
for use with
CHART FC2 - 66915

TUBE	Select	Load	Socket Notes	TUBE	Select	Load	Socket Notes
1AU2	A	100	14/A	6R-K19	D	3	14/E
1AY2	A	100	14/A	6R-P22	D	30	31
Insert leads into pins 4 & 5				7GS7	D	30	18
2HQ5	B	30	34	8GU7	E	38	15
3CN3	B	100	12/A	8JU8	E	32	17
3HQ5	B	30	34	8LT8	E	34	20/C
4AB8	C	32	18	8R-HP1	E	36	14
4HQ5	C	30	34	9GH8)	E	28	23
4JH6	C	33	34	9GH8)	E	27	14
4JL6	C	30	39	9R-AL1	E	50	30
4KN8	C	31	15	9R-HR2)	E	28	23
4M-P12	C	27	34	9R-HR2)	E	27	14
4M-P26	C	34	39	11HM7	F	28	31
4R-HH2	C	35	15	12BR3	F	30	14/E
4R-HH8	C	31	15	12FQ7	F	45	17
5GS7	C	30	18	12FX5	F	30	38
5JL6	C	30	39	12G-B3	F	29	3
5M-HH3	C	29	34	12G-K17	F	33	1
6CF8	D	33	18	12HL7	F	30	31
6CJ6	D	30	26	12R-K19	F	30	14/E
6DR4	D	36	34	12R-LL5	F	45	17
6G-B3	D	29	3	20AQ3	G	28	16/C/E
6GF7	D	30	15	21A6	G	27	26
6G-K17	D	30	1	50HN5	J	30	27
6HQ5	D	30	34	6939	F	35	25
6JH6	D	33	34	7551	E	35	31
6JL6	D	30	39	8417	D	30	3
6KN8	D	31	15	ECF805	D	29	18
6KS6	D	100	38/A	EL81	D	30	26
6LT8	D	34	20/C	LCF80	D	31	23
6LY8	D	35	24	LCL85	E	38	20
6ME8	D	30	25	LF183	C	27	31
6MG8	D	37	20	LF184	C	22	31
6M-HH3	D	26	34	PL81	G	27	26
6R3	D	31	13/E	XCL82	E	36	14
6R-HH2	D	30	15				
6R-HH8	D	31	15				

TUBE	Select.	Load	Socket	Notes	TUBE	Select.	Load	Socket	Notes	TUBE	Select.	Load	Socket	Notes
OA2	L	65	41	B	3A3	B	100	12	A	5AX4)	C	45	4	
OA3	L	70	10	B, C	3A4	B	37	35		5AX4)	C	45	5	
OB2	L	100	41	B, C	3AF4	B	31	40		5B8	C	36	23	
OB3	L	50	10	B, C	3AL5	B	36	36		5BC8	C	36	15	
OC2	L	50	41	A, B, C	3AU6	B	28	34		5BE8	C	31	20	
OC3	L	100	10	B, C	3AV6	B	34	34		5BK7	C	32	15	
OD3	L	45	10	B, C	3B2	B	100	12	D	5BQ7	C	36	15	
OZ4	L	32	10		3BA6	B	30	34		5BR8	C	31	20	
1A5	A	55	5		3BC5	B	27	34		5BS8	C	36	15	
1A7	A	60	5		3BE6	B	29	34		5BT8)	C	26	22	
1AF4	A	41	35		3BN4	B	26	38		5BT8)	C	43	27	
1AX2	A	100	13	D	3BN6	B	100	38	A	5BW8	C	26	25	
1B3	A	100	12	A	3BU8	B	30	22		5BZ7	C	33	15	
1C5	A	45	5		3BY6	B	29	34		5CG8	C	26	18	
1C7	A	72	5		3BZ6	B	27	34		5CL8	C	30	20	
1D5	A	66	3		3C6	A	100	29	D	5CM6	C	37	25	
1D8	A	38	7		3CB6	B	28	34		5CM8	C	37	20	
1DN5	A	49	35		3CE5	B	29	34		5CQ8	C	31	20	
1F5	B	45	5		3CF6	B	28	34		5CR8	C	36	20	
1G3	A	100	12	A	3CS6	B	29	34		5CZ5	C	31	25	
1G6	A	38	7		3CY5	B	27	34		5DH8	C	30	20	
1H2	A	100	13	D	3DK6	B	27	34		5EA8	C	32	20	
1H5)	A	51	4		3DT6	B	28	34		5EH8	C	25	21	
1H5)	A	45	5		3LF4	B	41	29		5J6	C	29	34	
1J3	A	100	12	A, D	3Q4	B	36	35		5R4)	C	50	4	
1J6	A	40	7		3Q5	A	53	5		5R4)	C	50	5	
1K3	A	100	12	A, D	3S4	B	41	35		5T4)	C	43	4	
1L4	A	50	35		3V4	B	39	35		5T4)	C	43	5	
1L6	A	66	35		4AU6	C	28	34		5T8)	C	49	19	
1LA4	A	47	29		4BA6	C	30	34		5T8)	C	28	25	
1LA6	A	54	28		4BC5	C	28	34		5U4)	C	50	4	
1LB4	A	47	29		4BC8	C	30	15		5U4)	C	50	5	
1LC5	A	40	29		4BE6	C	30	34		5U8	C	33	20	
1LC6	A	54	28		4BN6	C	100	38	A	5V3)	C	45	4	
1LD5	A	49	29		4BQ7	C	35	15		5V3)	C	45	5	
1LE3	A	45	29		4BS8	C	36	15		5V4)	C	35	4	
1LH4	A	49	29		4BU8	C	29	22		5V4)	C	35	5	
1LN5	A	47	29		4BX8	C	37	15		5V6	C	32	3	
1N5	A	49	5		4BZ6	C	30	34		5W4)	C	55	4	
1Q5	A	53	5		4BZ7	C	34	15		5W4)	C	55	5	
1R4	A	73	28		4BZ8	C	35	15		5X4)	C	50	6	
1R5	A	44	35		4CB6	C	26	34		5X4)	C	50	7	
1S4	A	39	35		4CE5	C	29	34		5X8	C	26	18	
1S5	A	49	35		4CS6	C	28	34		5Y3)	C	65	4	
1SA6	A	47	4		4CY5	C	27	34		5Y3)	C	65	5	
1T4	A	45	35		4DE6	C	26	34		5Y4)	C	65	6	
1T5	A	48	5		4DK6	C	27	34		5Y4)	C	65	7	
1U4	A	45	35		4DT6	C	28	34		5Z4)	C	35	4	
1U5	A	50	35		5AM8	C	35	16		5Z4)	C	35	5	
1U6	A	57	35		5AN8	C	51	15	A	6A8	D	36	3	
1V2	A	100	14	A	5AQ5	C	33	39		6AB4	D	27	34	
1X2	A	100	13	A	5AR4)	C	50	4		6AB7	D	33	2	
2AF4	B	28	40		5AR4)	C	50	5		6AC5	D	36	3	
2B3	B	100	12	A	5AS4)	C	50	4		6AC7	D	33	2	
2BN4	B	25	38		5AS4)	C	50	5		6AD6	D	100	3	B
2CY5	B	26	34		5AS8	C	33	17		6AD7	D	51	3	
2D21	D	35	39		5AT8	D	26	18		6AF3	D	30	14	E
2E26	D	36	8		5AU4)	C	55	4		6AF4	D	29	40	
2T4	B	30	40		5AU4)	C	55	5		6AF6	D	100	11	B
2V3	B	100	12	A	5AV8	C	51	16	A	6AG5	D	27	34	
3A2	B	100	13	A	5AW4)	C	55	4		6AG7	D	27	2	
					5AW4)	C	55	5						

TUBE	Select.	Load	Socket	Notes	TUBE	Select.	Load	Socket	Notes	TUBE	Select.	Load	Socket	Notes
6AH4	D	85	3		6BH8	D	32	24		6CM8	D	40	20	
6AH6	D	28	34		6BJ6	D	29	34		6CN7)	D	35	21	
6AJ4	D	26	32		6BJ7)	D	30	22		6CN7)	D	27	27	
6AJ5	D	42	34		6BJ7)	D	37	23		6CQ8	D	31	20	
6AJ8)	D	28	27		6BJ8)	D	32	22		6CR6	D	35	38	
6AJ8)	D	33	20		6BJ8)	D	40	26		6CR8	D	35	20	
6AK5	D	29	34		6BK4	D	75	11	A	6CS6	D	28	34	
6AK6	D	36	34		6BK5	D	31	21		6CS7	D	51	30	
6AL5	D	35	36		6BK7	D	30	15		6CU5	D	36	38	
6AL7	D	46	11		6BL4	D	30	7		6CU6	D	28	3	
6AM4	D	32	32		6BL7	D	40	1		6CU8	D	35	24	
6AM5	D	34	39		6BL8	D	28	23		6CX8	D	39	24	
6AM8	D	33	16		6BM8)	D	29	33		6CY5	D	27	34	
6AN4	D	25	40		6BM8)	D	31	14		6CY7	D	44	30	
6AN5	D	28	34		6BN4	D	26	38		6CZ5	D	32	25	
6AN8	D	51	15	A	6BN6	D	100	38	A	6DB5	D	38	25	
6AQ5	D	35	39		6BN8)	D	28	22		6DB6	D	28	34	
6AQ6	D	37	34		6BN8)	D	33	26		6DC6	D	28	34	
6AQ7	D	37	6		6BQ5	D	29	18		6DC8	D	29	18	
6AQ8	D	30	17		6BQ6	D	29	3		6DE6	D	26	34	
6AR5	D	38	34		6BQ7	D	30	15		6DE7	D	53	30	
6AS5	D	36	38		6BR8	D	32	20		6DG6	D	31	3	
6AS6	D	28	34		6BS8	D	35	15		6DJ8	D	31	17	
6AS7	D	33	1		6BT8)	D	43	27		6DK6	D	27	34	
6AS8	D	33	17		6BT8)	D	26	22		6DN6	D	32	9	
6AT6	D	34	34		6BU6	D	36	34		6DN7	D	48	1	
6AT8	D	26	18		6BU8	D	29	22		6DQ5	D	33	9	
6AU4	D	30	1		6BV8)	D	29	20	C	6DQ6	D	31	3	
6AU5	D	38	9		6BV8)	D	32	23		6DS5	D	32	39	
6AU6	D	27	34		6BW4	D	46	22		6DT5	D	37	25	
6AU7	D	43	17		6BW8	D	26	25		6DT6	D	28	34	
6AU8	D	36	24		6BX7	D	40	1		6DT8	D	30	17	
6AV5	D	30	9		6BX8	D	37	15		6EA8	D	32	20	
6AV6	D	32	34		6BY5	D	31	3	G	6EB8)	D	28	21	
6AW8	D	35	24		6BY6	D	28	34		6EB8)	D	40	24	
6AX4	D	32	1		6BY7	D	29	31		6EH5	D	28	38	
6AX5	D	37	3		6BY8)	D	30	17		6EH8	D	25	21	
6AX7	D	44	17		6BY8)	D	100	22	A	6EM5	D	32	25	
6AX8	D	31	20		6BZ6	D	30	34		6EW6	D	23	34	
6AZ8)	D	28	17	C	6BZ7	D	33	15		6F5	D	35	3	
6AZ8)	D	32	20		6BZ8	D	35	15		6F6	D	40	3	
6B4	D	49	5		6C4	D	34	34		6F8	D	39	3	
6B8	D	44	3		6C5	D	38	3		6G6	D	35	3	
6B-1000	D	30	34		6C8	D	39	3		6H6	D	69	8	
6BA6	D	29	34		6CA4	D	27	18		6J4	D	28	37	
6BA7	D	28	18		6CA5	D	35	38		6J5	D	34	3	
6BA8	D	34	24		6CA7	D	32	3		6J6	D	26	34	
6BC4	D	26	21		6CB5	D	32	9		6J7	D	39	3	
6BC5	D	26	34		6CB6	D	26	34		6J8	D	29	3	
6BC7)	D	28	22		6CD6	D	36	9		6K5	D	33	3	
6BC7)	D	32	23		6CE5	D	28	34		6K6	D	39	3	
6BC8	D	32	15		6CF6	D	28	34		6K7	D	40	3	
6BD4	D	60	3	A	6CG7	D	54	15		6K8	D	31	3	
6BD5	D	31	9		6CG8	D	28	18		6L6	D	38	3	
6BD6	D	33	34		6CH8	D	36	24		6L7	D	33	3	
6BE6	D	29	34		6CK4	D	28	4		6N7	D	33	3	
6BE8	D	31	20		6CL5	D	32	9		6Q7	D	34	3	
6BF5	D	38	39		6CL6	D	28	31		6R8)	D	49	19	
6BF6	D	39	34		6CL8	D	30	20		6R8)	D	28	25	
6BG6	D	32	9		6CM6	D	37	25		6S4	D	33	25	
6BH6	D	28	34		6CM7)	D	37	18		6S7	D	36	3	
					6CM7)	D	29	22						

TUBE	Select.	Load	Socket	Notes	TUBE	Select.	Load	Socket	Notes	TUBE	Select.	Load	Socket	Notes
6S8	D	38	6		7L7	D	30	28		12AV6	F	32	34	
6SA7	D	31	3		7N7	D	25	28		12AV7	F	33	17	
6SB7Y	D	29	3		7Q7	D	28	28		12AW6	F	31	34	
6SC7	D	34	6		7R7	D	31	28		12AX4	F	33	1	
6SD7	D	29	2		7S7	D	29	28		12AX7	F	44	17	
6SF5	D	37	6		7V7	D	37	28		12AY7	F	48	17	
6SF7	D	35	1	A	7W7	D	28	29		12AZ7	F	31	17	
6SG7	D	29	2		7X6	D	24	28		12B4	F	27	22	
6SH7	D	29	2		7X7	D	28	29		12B7	F	37	28	
6SJ7	D	32	2		7Y4	D	31	28		12BA6	F	29	34	
6SK7	D	34	2		7Z4	D	36	28		12BA7	F	27	18	
6SL7	D	54	1		8AU8	E	33	24		12BD6	F	33	34	
6SN7	D	47	1		8AW8	E	32	24		12BE6	F	27	34	
6SQ7	D	72	7		8BA8	E	34	24		12BE8	F	31	20	
6SR7	D	76	7		8BH8	E	32	24		12BF6	F	40	34	
6SS7	D	38	2		8BN8)	E	29	22		12BH7	F	36	17	
6SV7	D	44	1		8BN8)	E	33	26		12BK5	F	31	21	
6SZ7	D	80	7		8BQ5	E	29	18		12BL6	F	30	34	
6T4	D	28	40		8BQ7	E	30	15		12BN6	F	100	38	A
6T8)	D	50	19		8CG7	E	54	15		12BQ6	F	29	3	
6T8)	D	27	25		8CM7)	E	37	18		12BR7	F	32	17	
6U7	D	38	3		8CM7)	E	30	22		12BV7	F	29	31	
6U8	D	29	20		8CN7)	E	36	21		12BW4	F	46	22	
6V3	D	31	13	E	8CN7)	E	26	27		12BY7	F	29	31	
6V4	D	30	18		8CS7	E	55	30		12BZ7	F	32	17	
6V6	D	31	3		8CX8	E	38	24		12C5	F	35	38	
6V7	D	39	3		8EB8)	E	38	24		12C8	F	44	3	
6V8	D	32	31		8EB8)	E	28	21		12CA5	F	35	38	
6W4	D	29	1		8EM5	E	32	25		12CM6	F	37	25	
6W6	D	33	3		8SN7	E	47	1		12CN5	F	29	38	
6X4	D	32	34		9AU7	E	43	17		12CR6	F	34	38	
6X5	D	31	3		9BR7	E	37	17		12CS6	F	29	34	
6X8	D	25	18		9CL8	E	32	20		12CT8	F	43	15	A
6Y6	D	38	3		9U8	E	31	20		12CU5	F	33	38	
7A4	D	33	28		9X8	E	28	18		12CU6	F	31	3	
7A5	D	31	28		10C8	E	70	15	A	12CX6	F	25	34	
7A6	D	30	28		10DE7	E	50	30		12D4	F	29	1	
7A7	D	35	28		11C5	F	33	38		12DB5	F	31	25	
7A8	D	33	28		11CY7	F	44	30		12DE8)	F	35	22	A
7AD7	D	28	28		12A4	F	29	22		12DE8)	F	29	33	
7AF7	D	25	28		12A6	F	37	3		12DK7	F	30	25	
7AG7	D	28	28		12A8	F	36	3		12DL8)	F	30	33	
7AH7	D	27	28		12AB5	F	32	25		12DL8)	F	60	14	
7AU7	D	45	17		12AC6	F	34	34		12DQ6	F	32	3	
7B4	D	36	28		12AD6	F	29	34		12DQ7	F	28	31	
7B5	D	58	28		12AD7	F	42	17		12DS7)	F	85	14	
7B6	D	32	29		12AE6	F	37	34		12DS7)	F	40	27	A
7B7	D	37	28		12AE7	F	25	27		12DT5	F	37	25	
7B8	D	34	28		12AF3	F	30	14	E	12DT8	F	30	17	
7C4	D	51	28		12AF6	F	29	34		12DU7	F	27	25	
7C5	D	32	28		12AJ6	F	33	34		12DV8)	F	52	14	
7C6	D	35	29		12AL5	F	33	36		12DV8)	F	33	33	
7C7	D	31	28		12AL8)	F	16	33	A	12DZ6	F	26	34	
7E6	D	37	29		12AL8)	F	54	22		12ED5	F	30	38	
7E7	D	38	28		12AQ5	F	35	39		12EG6	F	28	34	
7EY6	E	30	3		12AT6	F	35	34		12EH5	F	28	38	
7F7	D	26	28		12AT7	F	30	17		12EK6	F	26	34	
7G7	D	40	28		12AU5	F	33	9		12EL6	F	32	34	
7H7	D	28	28		12AU6	F	28	34		12EM6	F	31	25	
7J7	D	28	28		12AU7	F	44	17		12EN6	F	30	3	
7K7	D	29	28		12AV5	F	30	9		12EZ6	F	26	34	

TUBE	Select.	Load	Socket	Notes	TUBE	Select.	Load	Socket	Notes	TUBE	Select.	Load	Socket	Notes
12F5	F	55	3		17AU5	G	38	9		50A5	J	29	28	
12F8)	F	75	23	A	17AV5	G	30	9		50B5	J	35	39	
12F8)	F	79	25		17AX4	G	32	1		50BK5	J	32	21	
12FM6	F	30	34		17BQ6	G	28	3		50BM8)	J	29	33	
12G4	F	33	34		17BY7	G	29	31		50BM8)	J	31	14	
12H6	F	69	8		17C5	G	35	38		50C5	J	33	38	
12J5	F	33	3		17CA5	G	35	38		50C6	J	34	3	
12J7	F	39	3		17CU5	G	33	38		50CA5	J	35	38	
12J8	F	25	25		17D4	G	30	1		50CD6	J	36	9	
12K5	F	29	38		17DQ6	G	27	3		50DC4	J	28	37	
12K7	F	37	3		17H3	G	33	22		50EH5	J	26	38	
12K8	F	31	3		17L6	G	31	3		50L6	J	28	3	
12L6	F	35	3		17R5	G	33	38		50X6	J	24	28	
12Q7	F	33	3		17W6	G	31	3		50Y6	J	31	3	
12R5	F	33	38		18A5	G	31	9		50Y7	J	38	8	
12S8	F	35	6		19AQ5	G	35	39		70L7)	J	43	2	A, C
12SA7	F	32	3		19AU4	G	31	1		70L7)	J	30	3	
12SC7	F	34	6		19BG6	G	31	9		117L7)	K	35	2	C
12SF5	F	35	6		19C8)	G	47	19		117L7)	K	31	3	
12SF7	F	33	1	A	19C8)	G	28	25		117M7)	K	35	2	C
12SG7	F	29	2		19J6	G	29	34		117M7)	K	32	3	
12SH7	F	29	2		19T8)	G	49	19		117N7	K	28	3	
12SJ7	F	33	2		19T8)	G	28	25		117P7	K	36	3	
12SK7	F	36	2		19V8	G	32	31		117Z3	K	29	39	
12SL7	F	54	1		19X8	G	28	18		117Z4	K	27	11	
12SN7	F	46	1		21EX6	G	30	9		117Z6	K	35	8	
12SQ7	F	72	7		25AC5	H	25	3		884	D	43	3	
12SR7	F	76	7		25AV5	H	32	9		1203A	D	51	28	
12SS7	F	38	2		25AX4	H	33	1		1232	D	33	28	
12SX7	F	48	1		25BK5	H	34	21		1611	D	37	3	
12U7	F	41	17		25BQ6	H	33	3		1620	D	38	3	
12V6	F	34	3		25C5	H	36	38		1622	D	39	3	
12W6	F	30	3		25CA5	H	35	38		1629	F	27	11	
12X4	F	31	34		25CD6	H	33	9		1852	D	36	2	
13DE7	F	50	30		25CU6	H	32	3		1853	D	30	2	
13DR7	F	44	30		25D4	H	29	1		2050	D	35	5	
14A4	F	33	23		25DN6	H	34	9		5654	D	41	34	
14A5	F	39	28		25DQ6	H	30	3		5691	D	49	1	
14A7	F	37	28		25DT5	H	37	25		5692	D	46	1	
14AE7	F	43	28		25EC6	H	29	9		5693	D	33	2	
14AF7	F	27	28		25EH5	H	28	38		5725	D	29	34	
14B6	F	33	29		25F5	H	35	38		5726	D	34	36	
14B8	F	32	28		25L6	H	35	3		5727	D	35	39	
14C5	F	33	28		25W4	H	31	1		5749	D	30	34	
14C7	F	31	28		25W6	H	30	3		5750	D	29	34	
14E6	F	37	29		25Z6	H	40	8		5751	F	46	17	
14E7	F	40	28		26A6	H	29	34		5814	F	42	17	
14F7	F	26	28		26C6	H	39	34		5844	D	25	34	
14H7	F	31	28		26D6	H	33	34		5879	D	41	18	
14J7	F	31	28		26Z5W	H	42	17		5881	D	39	3	
14N7	F	26	28		35A5	I	30	28		5963	F	44	17	
14Q7	F	29	28		35B5	I	32	39		5965	F	33	17	
14R7	F	30	28		35C5	I	31	38		6005	D	37	39	
14S7	F	29	28		35CD6	I	36	9		6058	D	35	36	
14V7	F	37	28		35L6	I	31	3		6066	D	34	34	
14W7	F	28	29		35W4	I	29	37		6095	D	37	39	
14X7	F	30	29		35Y4	G	28	29		6096	D	41	34	
14Y4	F	31	28		35Z3	I	28	29		6099	D	28	34	
16A8)	G	29	33		35Z4	I	28	11		6101	D	29	34	
16A8)	G	31	14		35Z5	I	26	11		6136	D	27	34	
17A5	G	32	9		45Z3	J	33	39		6146	D	26	11	

TUBE	Select.	Load	Socket	Notes	TUBE	Select.	Load	Socket	Notes	TUBE	Select.	Load	Socket	Notes
6201	F	30	17		ECF80	D	28	23		VR90	L	53	10	B,C
6202	D	32	34		ECF82	D	34	20		VR105	L	100	10	B,C
6267	D	33	18		ECH81)	D	28	27		VR150	L	45	10	B,C
6550	D	39	3		ECH81)	D	33	20		VT90	D	72	8	
6660	D	30	34		ECL82)	D	31	14		X17	A	44	35	
6661	D	29	34		ECL82)	D	29	33		X155	D	35	15	
6662	D	29	34		ED2	D	35	36		XXB	A	100	29	D
6663	D	34	36		EF86	D	33	18		XXD	F	29	28	
6669	D	35	39		EF93	D	29	34		XXFM	D	32	29	
6677	D	29	31		EF94	D	27	34		XXL	D	33	28	
6679	F	31	17		EF95	D	29	34		ZD17	A	49	35	
6680	F	41	17		EF96	D	27	34		ZD19	A	49	35	
6681	F	42	17		EH90	D	28	34						
6973	D	35	33		EK90	D	29	34						
7025	F	49	17		EL34	D	32	3						
7119	F	25	18		EL37	D	39	3						
7189	D	29	18		EL84	D	29	18						
7193	D	31	3	F	EL90	D	35	39						
8016	A	100	12	A	EL91	D	34	39						
9001	D	36	34		EM80	D	53	25						
9002	D	37	40		EM81	D	55	25						
9003	D	34	34		EY81	D	31	13	E					
9006	D	51	37		EZ35	D	31	3						
B36	F	46	1		EZ80	D	30	18						
B65	D	47	1		EZ81	D	33	18						
B152	F	30	17		EZ90	D	32	34						
B309	F	30	17		GZ32)	C	35	4						
B329	F	44	17		GZ32)	C	35	5						
BPMO4	D	35	39		GZ34)	C	50	4						
D77	D	35	36		GZ34)	C	50	5						
D152	D	35	36		H52)	C	50	4						
DAF91	A	49	35		H52)	C	50	5						
DAF92	A	50	35		HBC90	F	35	34						
DD6	D	35	36		HBC91	F	32	34						
DF904	A	45	35		HF93	F	29	34						
DH77	D	34	34		HF94	F	28	34						
DK91	A	44	35		HK90	F	27	34						
DL94	B	39	35		HL92	J	33	38						
DP61	D	29	34		HMD4	D	29	34						
DY30	A	100	12	A	HY90	I	29	37						
DY80	A	100	13	A	KT32	H	35	3						
DY87	A	100	13	A	KT66	D	26	3						
E182CC	F	25	18		L63	D	34	3						
EAA91	D	35	36		L77	D	34	34						
EABC80)	D	50	19		N19	B	39	35						
EABC80)	D	27	25		N77	D	35	36						
EB91	D	35	36		PCL82)	G	29	33						
77501	D	34	34		PCL82)	G	31	14						

PJL COMMENT HP LaserJet 4V Driver

@PJL COMMENTWin95 2.1.0.0s

@PJL SET RESOLUTION